

LAMPIRAN

1. Tabel Vektor Interrupt

Sumber Interrupt	Keterangan	Asal	Nomor Vektor	IPR
NMI	Non Maskable Interrupt		7	
IRQ0		Pin Eksternal	12	IPRA7
IRQ1			13	IPRA6
IRQ2			14	IPRA5
IRQ3			15	
IRQ4			16	IPRA4
IRQ5			17	
WOVI			Interval Timer	Watchdog Timer
CMI	Compare Match	Refresh Controller	21	
IMIA0	Compare Match/ Input Capture A0	ITU Channel 0	24	IPRA2
IMIB0	Compare Match/ Input Capture B0		25	
OVI0	Overflow 0		26	
IMIA1	Compare Match/ Input Capture A1	ITU Channel 1	28	IPRA1
IMIB1	Compare Match/ Input Capture B1		29	
OVI1	Overflow 1		30	
IMIA2	Compare Match/ Input Capture A2	ITU Channel 2	32	IPRA0
IMIB2	Compare Match/ Input Capture B2		33	
OVI2	Overflow 2		34	
IMIA3	Compare Match/ Input Capture A3	ITU Channel 3	36	IPRB7
IMIB3	Compare Match/ Input Capture B3		37	
OVI3	Overflow 3		38	
IMIA4	Compare Match/ Input Capture A4	ITU Channel 4	40	IPRB6
IMIB4	Compare Match/ Input Capture B4		41	
OVI4	Overflow 4		42	
DEND0A		DMAC	44	IPRB5
DEND0B			45	
DEND1A			46	
DEND1B			47	
ERI0	Receive Error 0	SCI Channel 0	52	IPRB3
RXI0	Receive Data Full 0		53	
TXI0	Transmit Data Empty 0		54	
TEI0	Transmit End 0		55	
ERI1	Receive Error 1	SCI Channel 1	56	IPRB2
RXI1	Receive Data Full 1		57	
TXI1	Transmit Data Empty 1		58	
TEI1	Transmit End 1		59	
ADI	A/D End	A/D	60	IPRB1